

# FS Series Motor Controller

## Instruction & Installation Manual



## ***Functions and Features***

***The following is a list of available features not included in every control. See ordering instructions for how to order listed features.***

### **Standard Features:**

#### **Controlled Acceleration**

An adjustable function that allows smooth acceleration on vehicles of varying weights and speeds.  
See potentiometer adjustments on page 3.

#### **Current Limit**

An adjustable function that renders self-protection to the control and the traction motor.  
See potentiometer adjustments on page 3.

#### **Thermal Protection**

A protection circuit that reduces control output, if needed, to maintain rated component temperature. Switching frequency is reduced at ~ 60° C.

#### **Accelerator Volts Hold Off (Option)**

This feature assures that the accelerator is calling for low speed operation at start up.

#### **Plug Braking (Option)**

An adjustable function that allows smooth braking on vehicles of varying weights and speeds.  
See potentiometer adjustments on page 3.

#### **High Frequency Operation**

This feature provides oscillation frequency of 13 kHz. The high oscillation rate allows for quieter operation, higher average motor current with lower peak motor currents, less ripple current at the motor, and less motor heating.

#### **Reversed Battery Protection**

(With Line Contactor and Diode) This function disables the operation of the control if the battery connections are reversed.

#### **Low Voltage**

The control is designed for use down to the following voltages:

24/36V: 16V cutout

36/48V: 19V cutout

48/72V: 25V cutout

72/96V: 36V cutout

120/144V: 60V cutout

The control will not operate when the cutout voltage is reached.

## ***Specifications\****

Package dimensions: .....	6.75" L x 5.75" W x 2.80" H size 'S'
.....	8.75" L x 5.75" W x 2.80" H size 'L'
.....	See Outline Below
Maximum armature current: .....	480 Amps size 'S'
.....	700 Amps size 'L'
Maximum plug current .....	300 A for 3 sec 'S'
.....	450 A for 3 sec 'L'
Operating temperature .....	-40°C to +50°C
Storage temperature .....	-40°C to +85°C
Thermal Protection .....	90°C

Accelerator Input .....	5k to 0 Ohms, 0 to 5k Ohms, ..... 0-5V (3 wire) or Special config.
Power Devices .....	MOSFETS
Motor Reversing .....	Contactors or Manual Switch
Operating frequency (Armature): .....	13 kHz
Modulation .....	PWM
Adjustment Method .....	Trimpot
Reverse Battery Protection .....	With Line Contactor
Low Battery Operation .....	Yes
Accelerator Volts Hold Off .....	Yes

\* Specifications list typical functions and features that are available. Actual control feature content will vary, depending on application needs.

## ***Installation Tips:***

Using heat transfer compound (FSIP P/N: 43-8012-30) between the motor control and the mounting plate of the vehicle will enhance performance on heavy-duty applications. A thin coating that covers the mounting surface gives the best heat transfer.

- Always use safe practices while working on electric vehicles.
- When appropriate, lift the drive wheels off the ground.
- Disconnect the batteries before removing or installing controllers.
- Verify all electrical connections are secure. Improper connections will cause heat and could damage drive system.

## ***Warranty and Service***

This product is covered by a 12-month warranty. Worldwide technical assistance and service are available from local FSIP representatives.

**Ordering Information:**

**Part Number**

51-            42            L            700            N            H            0            S  
 BASIC    ARG 1            ARG 2            ARG 3            ARG 4            ARG 5            ARG 6            ARG 7

**ARG 1 Voltage**

30 - 24 to 36 VDC  
 42 - 36 to 48 VDC  
 48 - 48 VDC  
 60 - 48 to 72 VDC  
 72 - 72 VDC  
 84 - 72 to 96 VDC  
 HV - 120 to 144 VDC

**ARG 4 Plugging Option**

P - Plugging  
 N - No Plugging

**ARG 2 Unit Size**

S - 5.75" X 6.75" X 2.8"  
     Imax    VDC  
     500    24 through 72V  
  
 L - 5.75" X 8.75" X 2.8"  
     Imax    VDC  
     700    24 through 72V  
     600    72 through 96V  
     125    120 through 144V

**ARG 5 Accelerator Volts Hold Off**

H - Unit has Hold Off  
 N - No Hold Off

**ARG 6 Accelerator Input**

0 - 0 to 5K Ohms  
 5 - 5K to 0 Ohms  
 V - 3-wire 5k pot,  
     Club Car V-Glide  
 S - Special setting

**ARG 7 Features**

S - Standard  
 P - Premium

**ARG 3 Current Limit (examples)**

275 - 275 Amps  
 500 - 500 Amps  
 600 - 600 Amps  
 700 - 700 Amps

**Potentiometer Adjustment.**


The potentiometers are designed to be adjusted with a small trimmer or screwdriver.

Current Limit (CL) - Adjust potentiometer CW (clockwise) to increase maximum current limit. The current is adjustable from approximately 50% to 100% of controller rating.


Controlled Acceleration (CA) - Adjust potentiometer CW to increase acceleration. The acceleration ramp is adjustable from approximately 0.5 to 5 seconds. The factory setting is 1.2 seconds.

Plugging Adjustment (PL) - Adjust potentiometer CW to increase intensity of plugging. Be sure when setting Plugging to make for smooth forward to reverse transition. Plugging current is adjustable from approximately 10% to 100% of specified limit.


**Outline (For Reference Only)**




*Elementary Diagrams (For Reference Only)*



Typical EV wiring with F & R Contactors, Hold Off option (2-wire Accelerator shown)  
Dotted line shows units with optional Plugging



Typical Golf Car wiring with F & R switch, no Hold Off option (3-wire Accelerator shown)  
Dotted line shows units with optional Plugging



MS2 is closed when directional selector sw is in FWD or REV  
 MS3 is activated by accelerator pedal  
 MS4 is closed by directional selector switch in REV only

Optional Plug  
 Connection to  
 Motor A2

Typical EZGO Golf Car wiring with F & R switch using ITS Converter